

2.4mm & 1.85mm Automated Tuners

DATA SHEET / 4T-050G04A

MODELS:
MT984AL01
MT985AL01




What is load pull?


Load Pull is the act of presenting a set of controlled impedances to a device under test (DUT) and measuring a set of parameters at each point. By varying the impedance, it is possible to fully characterize the performance of a DUT and use the data to:

- > Verify simulation results of a transistor model (model validation)
- > Gather characterization data for model extraction (behavioral model extraction)
- > Design amplifier matching networks for optimum performance (amplifier design)
- > Ensure a microwave circuit's ability to perform after being exposed to high mismatch conditions (ruggedness test)
- > Confirm the stability or performance of a microwave circuit or consumer product under non-ideal VSWR conditions (stability/performance/conformance/antenna test)


Example of load pull measurements with Output Power (Pout) contours plotted on a Smith Chart.



*Iso Pout Contours
Measured @ 1.85 GHz*




*Iso Pout Contours
Simulated @ 1.85 GHz*




Slide-Screw Impedance Tuner

One tool available to vary the impedances presented to a DUT is the slide-screw impedance tuner. The slide-screw tuner is based on a 50Ω slabline and a reflective probe, sometimes referred to as a slug. Ideally, when the probe is fully retracted, the tuner presents a near- 50Ω impedance represented by the center of a normalized Smith Chart. As the probe is lowered into the slabline (Y-direction) it interrupts the electric field that exists between the center conductor and walls of the slabline, reflects some


of the energy back towards the DUT, creates a capacitance and increases the magnitude of reflection (represented by the red curve on the Smith Chart at right). As the probe travels along the slabline (X-direction), the distance between the probe and the DUT is altered, thereby rotating the phase of the reflection (represented by the blue curve on the Smith Chart). It is therefore possible to recreate nearly any arbitrary impedance without the need of discrete components (lumped elements or transmission lines).



Simplified representation of a slide-screw tuner.



The probes used in slide-screw tuners are wideband in nature, and have similar reflective properties over a wide range of frequencies. In order to increase the overall useful bandwidth of the tuner, two probes of varying dimensions are independently used within a tuner; one for low frequencies and one for high frequencies. In this manner, it is common for slide-screw tuners to achieve an overall frequency range of several octaves to over a decade.



VSWR versus Frequency of a two-probe slide-screw tuner.


Pre-Calibration (Pre-Characterization)

Slide-screw tuners are available in both manual and automated varieties. While they both work on the same principle and capacitive probe technique, automated tuners have the ability to be pre-calibrated. Pre-calibration involves recording the s-parameters of each probe at varying X and Y positions for the frequencies of interest using a calibrated vector network analyzer. In general, X and Y positions are selected such that an even distribution of impedances are recorded over the Smith Chart. Once the calibration data is stored in a lookup table, the VNA is no longer required to use the tuner; the tuner 'knows' how to present impedances accurately without VNA verification.

Tuner Repeatability

Tuner repeatability is defined as the vector difference between the pre-calibrated s-parameter data and subsequent s-parameter measurements after movement, when returning the probe to a given X and Y position. Since the impedances presented to the DUT are reliant on the tuner's ability to accurately return to pre-calibrated states, repeatability is a critical tuner characteristic that affects the reliability of measurement data. In order to guarantee a high level of repeatability, precision

mechanics and motors within the tuner are used to return the probe to its pre-calibrated positions with s-parameter vector differences of -40 to -50 dB or better (see specific tuner model pages 6 through 8 for typical repeatability graphs).




Tuning Accuracy and Interpolation

During pre-calibration, the tuner's s-parameters are recorded at a user-definable number (normally between 300-3000) of X and Y positions giving an even distribution over the Smith Chart. However, an arbitrary load impedance that falls between pre-calibrated states might be required. To achieve a high level of accuracy, a two-dimensional algorithm is used to interpolate between the closest pre-calibrated impedances

in order to determine the new physical X and Y positions of the desired interpolated impedance. Interpolation increases the number of tunable impedances well beyond the initial pre-calibration range.

Given a sufficiently dense pre-calibration look-up table, a tuner's repeatability (ability to return to pre-calibrated states) and accuracy (ability to interpolate between pre-calibrated states) offer similar performances.



Patented Embedded Tuner Controller

(U.S. Patent No. 8,823,392)

All Maury slide-screw automated impedance tuners are equipped with a patented embedded controller (U.S. Patent No. 8,823,392) with onboard microprocessor and memory. After pre-calibration, the lookup table is copied onto the tuner's embedded flash memory storage, as are any s-parameter files of passive components that will be used with the tuner (adapters, cables, fixtures,

probes, attenuators...). The tuner's onboard microprocessor will use the lookup table and component s-parameter blocks to calculate the probe positions required to present an arbitrary load impedance taking into account (de-embedding) all adapter/fixture losses between the tuner and DUT, and all back-side losses between the tuner and the measurement instrument, as well as possible non-50Ω terminations.

An integrated web interface allows for easy point-and-click tuning. Simply open Internet Explorer, Firefox, Chrome or any

web browser in any operating system, and begin tuning. Capabilities include a graphic interface for de-embedded tuning at the DUT reference.

Direct ASCII commands can be sent through raw TCP/IP interface over Ethernet or USB and used with any socket programming language or through any Telnet client program in any operating system. Commands include direct impedance tuning, reference-plane shifting, VSWR testing and more.

Parameter	Value
Manufacturer	Maury Microwave Corporation
Instrument Model	MT982-EL30
Serial Number	5270
Firmware Revision	3.4-1.24
Description	Maury MT982-EL30 - 5270
LXI Extended Features	LXI Core Functions
LXI Version	1.4
mDNS-Hostname	169.254.6.77, MT982-EL30-5270.local
IP Address	169.254.6.77
MAC Address	fc:6c:31:00:00:e6
Device Address	TCPIP0::169.254.6.77::5025::SOCKET
Telnet Address	telnet://169.254.6.77:5024

Parameter	Currently in use
VXI-11 Discovery	On
mDNS Discovery	On
DHCP	On
Auto-IP	On
Network-Hostname	MT982-EL30-5270.local
IP Address	169.254.6.77
Netmask	255.0.0.0
Gateway	0.0.0.0
Dynamic DNS Updates	On
Manual DNS	Off
Domain	Belkin
Primary DNS	10.10.1.17
Secondary DNS	10.10.1.19
Description	Maury MT982-EL30 - 5270
Web Password	hidden

Edit Configuration

Tuning | Position Control | Constant VSWR | Test Setup | Tuner Config

THRU MT982EL30_5270... THRU

DUT Frequency 0.800000 Please select Frequency

Harmonics 0

Frequency	0.800000 GHz
Gamma (DUT)	0.506 122.5
#	S11 S11 S12 S12 S21 S21 S22 S22
Mag	Mag Pha Mag Pha Mag Pha Mag Pha
Total	0.506 122.5 0.852 8.2 0.852 8.2 0.509 73.5
Fixture	0.000 0.0 1.000 0.0 1.000 0.0 0.000 0.0
Tuner	0.506 122.5 0.852 8.2 0.852 8.2 0.509 73.5
Back	0.000 0.0 1.000 0.0 1.000 0.0 0.000 0.0
Termination	0.000 0.0

Refresh

Setup File

Save Recall Clear

Tuning | Position Control | Constant VSWR | Test Setup | Tuner Config

Format Gamma, Phase

0.800000 GHz Gamma Phase

Targets 0.006 -101.690

Initialize Tuner Tune

Tuning Information

- Gamma, Phi, Loss
 - 0.800000 0.006, -101.69, 0.048dB
- R + jX, Loss
 - 0.800000 49.864 - j0.635 0.048dB
- VSWR (Phi) Loss
 - 0.800000 1.01:1 (-101.69*) 0.048dB
- Motor Position
 - Motor 1 100
 - Motor 2 5000
 - Motor 3 5000

Zoom 1x

#	Freq GHz	S11 Mag	S11 Pha	S12 Mag	S12 Pha	S21 Mag	S21 Pha	S22 Mag	S22 Pha	Loss dB
#	0.800000	0.006	-101.7	0.994	21.0	0.994	21.0	0.007	-29.9	0.048

Show SPAR Refresh

MTUNE Tuner Characterization and Control Software

Introduction

MTUNE is a software package that allows device calibration/characterization and control of multiple tuner configurations for automated impedance tuning. It may be used in any application requiring the ability to match the impedance of a microwave circuit element or to establish specific impedances at a terminal interface at various frequencies. The software provides a standalone server (API) for remote communication for advanced use as well as interactive user interface to guide the user through the calibration and tuning process.


Software Features:

- > Desktop and cloud-based applications enhances user flexibility
- > Modern wizard-driven GUI with support for most commercial VNAs
- > Automatic instrument identification for easy setup
- > Stay up-to-date with software update reminders
- > Enhanced user support with direct ticketing and error logging

New and Updated Capabilities:

- > Faster multi-frequency tuner characterization
- > New tuner characterization validation process
- > Enhanced frequency interpolation
- > New non-harmonically related multi-frequency impedance tuning

MTUNE3 is compatible with all MT-series and XT-series tuners with embedded controllers, and can be downloaded from https://www.maurymw.com/MW_RF/MTUNE.php



2.4mm & 1.85mm Automated Tuners

Available Models

Model	Frequency Range (GHz)	Matching Range		Power Capability ²	Vector Repeatability (Minimum)	Insertion Loss (Probes Fully Retracted)	Connector Type	Mating Surface Dimensions
		Minimum	Typical ¹					
MT984AL01	8.0 – 50.0	10:1	20:1	10 W CW 100 W PEP	-40 dB	0.60 dB	2.4mm	5.47" [13.88 cm]
MT985AL01	8.0 – 65.0	10:1	20:1	10 W CW 100 W PEP		1.15 dB	1.85mm	

¹ Defined as the minimum VSWR over 70% of the frequency range.

² Power rated at maximum VSWR.

Accessories Provided

Each tuner is provided with one (1) MT1020F power supply, one (1) USB cable, one (1) Ethernet cable, one (1) USB to Ethernet adapter, and one (1) operating manual.

Recommended Accessories

8799A1 Torque Wrench

Recommended for tightening all 3.5mm, 2.92mm, 2.4mm & 1.85mm precision connectors to the proper in. lbs without over-torquing the connection.

A048A 2.4mm/1.85mm Digital Connector Gage Kit

Recommended for checking the critical interface dimensions of precision 2.4mm & 1.85mm connectors. Digital indicator style.




8799A1




A048A

Exemplary Performance Data for Model MT984AL01 2.4mm Automated Tuners



VSWR versus Frequency for MT984AL01 automated tuners.



Repeatability for MT984AL01 automated tuners.



MT984 AL01

*U.S. Patent No. 8,823,392
International Patents Pending*

Specifications

Frequency Range -- 8.0 to 50.0 GHz
VSWR Matching Range
Minimum -- 10:1
Typical -- 20:1¹
Step Size (Probes) -- 31 microinches²
Step Size (Carriage) -- 50 microinches²
Connectors -- Precision 2.4mm, M/F³

Power Capability -- 10W CW; 100W PEP⁴
Vector Repeatability (Min.) -- -40 dB
Insertion Loss (probes fully retracted) -- 0.60 dB


¹ Defined as the minimum VSWR over 70% of the frequency range.

² Based on 1/2 stepping the drive motors.


³ Precision 1.85mm per Maury data sheet 5E-064.

⁴ Power rated at maximum VSWR.

Exemplary Performance Data for Model MT985AL01 1.85mm Automated Tuners



VSWR versus Frequency for MT985AL01 automated tuners.



Repeatability for MT985AL01 automated tuners.



MT985 AL01

*U.S. Patent No. 8,823,392
International Patents Pending*

Specifications

Frequency Range -- 8.0 to 65.0 GHz
VSWR Matching Range
Minimum -- 10:1
Typical -- 20:1¹
Step Size (Probes) -- 31 microinches²
Step Size (Carriage) -- 50 microinches²
Connectors -- Precision 1.85mm, M/F³

Power Capability -- 10W CW; 100W PEP⁴
Vector Repeatability (Min.) -- -40 dB
Insertion Loss (probes fully retracted) -- 1.15 dB


¹ Defined as the minimum VSWR over 70% of the frequency range.

² Based on 1/2 stepping the drive motors.


³ Precision 1.85mm per Maury data sheet 5E-089.

⁴ Power rated at maximum VSWR.

MT984AL01 /
MT985AL01
Dimensions in
Inches [cm]



VISIT OUR WEB STORE
TO LEARN MORE ABOUT
OUR PRODUCTS



www.maurymw.com



CONTACT US:

W / maurymw.com
E / maury@maurymw.com
P / +1-909-987-4715
F / +1-909-987-1112
2900 Inland Empire Blvd
Ontario, CA 91764

